

1 DESCRIPTION

CBL4004 is used for analog audio connections on the AudioScience ASI67xx and ASI57xx series of cards. It has 2 connectors. One end of the cable has one VHDCI connector that plugs into the upper VHDCI connector on the card. On the other end of the cable there is one Centronics connector that can be plugged in to a CBL1044 to provide XLR connectors for the analog audio inputs and outputs.

2 PINOUTS

2.1 50pin Centronics audio - female

Left In 1-	1	26	Left In 1+
Right In 1-	2	27	Right In 1+
Left In 2-	3	28	Left In 2+
Right In 2-	4	29	Right In 2+
Left In 3-	5	30	Left In 3+
Right In 3-	6	31	Right In 3+
Left In 4-	7	32	Left In 4+
Right In 4-	8	33	Right In 4+
Right Out 4-	9	34	Right Out 4+
Left Out 4-	10	35	Left Out 4+
Right Out 3-	11	36	Right Out 3+
Left Out 3-	12	37	Left Out 3+
Right Out 2-	13	38	Right Out 2+
Left Out 2-	14	39	Left Out 2+
Right Out 1-	15	40	Right Out 1+
Left Out 1-	16	41	Left Out 1+
Right Out 5-	17	42	Right Out 5+
Left Out 5-	18	43	Left Out 5+
Right Out 6-	19	44	Right Out 6+
Left Out 6-	20	45	Left Out 6+
Right Out 7-	21	46	Right Out 7+
Left Out 7-	22	47	Left Out 7+
Right Out 8-	23	48	Right Out 8+
Left Out 8-	24	49	Left Out 8+
Ground	25	50	Ground

2.2 68pin VHDCI - male

