

1 DESCRIPTION

CBL4005 is used to connect the AudioScience ASI67xx and ASI57xx series of cards to a Radio Systems Hub-12 breakout box for analog connections. It has 2 connectors, one VHDCI that plugs into the upper connector on the card and one HD50 the plugs into the analog connector on the Hub-12.

2 PINOUTS

2.1 HD50 - Male

Left In 1-	1	26	Left In 1+
Right In 1-	2	27	Right In 1+
Left In 2-	3	28	Left In 2+
Right In 2-	4	29	Right In 2+
Left In 3-	5	30	Left In 3+
Right In 3-	6	31	Right In 3+
Left In 4-	7	32	Left In 4+
Right In 4-	8	33	Right In 4+
Right Out 4-	9	34	Right Out 4+
Left Out 4-	10	35	Left Out 4+
Right Out 3-	11	36	Right Out 3+
Left Out 3-	12	37	Left Out 3+
Right Out 2-	13	38	Right Out 2+
Left Out 2-	14	39	Left Out 2+
Right Out 1-	15	40	Right Out 1+
Left Out 1-	16	41	Left Out 1+
Right Out 5-	17	42	Right Out 5+
Left Out 5-	18	43	Left Out 5+
Right Out 6-	19	44	Right Out 6+
Left Out 6-	20	45	Left Out 6+
Right Out 7-	21	46	Right Out 7+
Left Out 7-	22	47	Left Out 7+
Right Out 8-	23	48	Right Out 8+
Left Out 8-	24	49	Left Out 8+
Ground	25	50	Ground

2.2 68pin VHDCI analog - Male

